



CFG6/En
 GND -> Driver enabled
 Vio -> Driver disabled
 Open -> Driver enabled with ramp down from 100% to 34% after about 3s

CFG2	CFG1	Steps	Interpolation	Chopper	Mode
GND	GND	1	No		spreadCycle
GND	Vio	2	No		spreadCycle
GND	Open	2	Yes to 256		spreadCycle
Vio	GND	4	No		spreadCycle
Vio	Vio	16	No		spreadCycle
Vio	Open	4	Yes to 256		spreadCycle
Open	GND	16	Yes to 256		spreadCycle
Open	Vio	4	Yes to 256		stealthChop
Open	Open	16	Yes to 256		stealthChop

Released under the Creative Commons Attribution Share-Alike License <http://creativecommons.org/licenses/by-sa/4.0/>
 Designed by Stephan Watterott (Watterott electronic)
 Based on the Trinamic TMC2100-BOB

Switch Science, Inc.
 SilentChopStick
 2015/04/10 10:14:52
 Sheet: 1/1